

SMATV SPLITTER

MODEL:CS32T

DESCRIPTION: 3 Input 2 Way Splitter



Featrues:

- Built-in amplifier
- Low insertion loss
- High isolation and return loss
- Output ports -input ports DC Pass
- Sheet metal housing with plastic holder
- Design good for indoor usage

Specifications

Item		Specifications	Remark
Frequency Range	Terr.	47~862MHz	
	SAT	950~2150MHz	
Inputs		2 SAT+1 Terr.	F connectors
Outputs		2×2 SAT+2×1 Terr.	F connectors
Insertion Loss	Terr.	15dB	Gain
	SAT	15dB	Gain
Adjustable Range	Terr.	15dB	
	SAT	15dB	
Return Loss	Terr.	12dB	
	SAT	12dB	
Isolation	OUT-OUT	30dB	
	OUT-TAP	30dB	
Power Supply		IN: 90~264V OUT:18V 500mA	
Dimensions (w,d,h)		118×115×52	mm