

SMATV TAP

MODEL:CT172T

DESCRIPTION: 17 Input 2 Way TAP



Featrues:

- Built-in amplifier
- Low insertion loss
- High isolation and return loss
- Sheet metal housing with plastic holder
- Design good for indoor usage

Specifications

Item		Specifications	Remark
Frequency Range	Terr.	47~862MHz	
	SAT	950~2150MHz	
Inputs		16 SAT+1 Terr.	F connectors
Outputs		16 SAT+1 Terr.	F connectors
TAP		2×16 SAT+2×1 Terr.	F connectors
Thru Loss	Terr.	1dB	
	SAT	1dB	
TAP Loss	Terr.	6dB	Gain
	SAT	6dB	Gain
Adjustable Range	Terr.	15dB	
	SAT	15dB	
Return Loss	Terr.	12dB	
	SAT	12dB	
Isolation	OUT-OUT	30dB	
	OUT-TAP	30dB	
Power Supply		IN: 90~264V OUT:18V 2500mA	
Dimensions (w,d,h)		370×120×52	mm